You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7. Electrical Parts List

7-1 CS29Z6HPGX/BWT

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY CHASSIS	
1		AA91-04827A	ASSY CHASSIS;CS29Z6HPGX/BWT,K55A	S.N.A
2	C-BLOC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
2	D-FOCU	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
2	MP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
2	PCB	AA61-00706B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
2	TBA+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
2	WP+HC	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
2		AA94-08584P	ASSY PCB MISC-CRT;29Z6,K55A,100HZ	
3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
3	C523	2306-000272	C-FILM,MPPF;820nF,5%,400V,BK,29x25.5x18.	
3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,400MM,35155-0800	
3	GT501A	AA39-00341A	LEAD CONNECTOR;K55A(WT-32Z4HD),UL1015#18	
⚠ 3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
4		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ 3	V999S	3704-001032	SOCKET-CRT;8P,29PI,35.5PI,AU30U	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3		AA97-12040A	ASSY AUTO-CRT;CS29Z6HP,K55A	S.N.A
4	C501	2201-000193	C-CERAMIC,DISC;0.01NF,0.25PF,50V,C0G,TP,	
4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
4	C510	2201-000291	C-CERAMIC,DISC;1NF,10%,500V,Y5P,TP,7.5X3	
4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
4	C513	2201-000600	C-CERAMIC,DISC;0.56NF,10%,50V,Y5P,TP,5X3	
4	C514	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4	C515	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	CF02	2201-000017	C-CERAMIC,DISC;1NF,10%,50V,Y5P,TP,5X3.5M	
4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
4	CF04	2201-000516	C-CERAMIC,DISC;4.7NF,+100-0%,500V,Y5U,TP	
4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
4	CF07	2201-000604	C-CERAMIC,DISC;0.056NF,+100-0%,500V,SL,T	
4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	
4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
4	DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
4	DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
4	FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
4	LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
4	Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R503	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R508	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R509	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	
4	R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
4	R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
4	R516	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
4	R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
4	R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
4	R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
4	R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R561	2001-001126	R-CARBON(S);300OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
4	RF13	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
4	RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
4	RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
4	RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
4	RF17	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	RF18	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	RF19	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
4	RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
4	RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
4	RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
4	RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
4	RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	

Level	Loc. No.	Code No.	Description ; Specification	Remark
2		AA96-00908E	ASSY COVER P-TERMINAL BOARD;29Z6,CIS,HIP	
3		AA64-02823A	INLAY-T/BOARD;Z7,PS SHEET,T0.5,PAL	S.N.A
3		AA65-00025A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
2		AA94-11750A	ASSY PCB MISC-A/V SIDE;29Z6,K55A,PAL	
3	AV+CV	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
3	CN701	AA39-00317B	LEAD CONNECTOR-ASSY;K55A/WT-32Z4HD,UL100	
3	CN703	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
3	CN704	AA39-00070B	LEAD CONNECTOR-ASSY;,4P,500MM,YBNH250-04	
3	JA701	3722-001164	JACK-PIN;3P,3.4mm,SN,WH:YE:RE,#16-22	
3	JK04	3722-000544	JACK-VHS;4P,11.5mm,AG,BLK,N	
3	JKH701	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	
3		AA97-12697A	ASSY AUTO-A/V SIDE;,K55A,PAL,29Z6	S.N.A
4	C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
4	C707	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	C708	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m	
4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L705	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
4	L706	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
4	L707	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L708	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	PCB	AA41-00620B	PCB-A/V SIDE(Z7);CT-29Z7HR,FR-1,1L,B,1.6	S.N.A
4	R701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
3		AA96-00938B	ASSY COVER P-COVER A/V;29Z6,CIS,HIPS HB,	
4		AA63-60001R	SPACER-FELT;-,FELT,-,-,-,-,T0.35,-,200X1	S.N.A
4		AA64-02667B	INLAY-AV;Z7,PS SHEET,T0.3,DGN-K189,K55A	S.N.A
4		AA63-00571A	COVER-A/V;29Z6,HIPS,HB,G4309,DGN-1189	S.N.A
3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
2		AA94-08584Q	ASSY PCB MISC-CONTROL;29Z6,K55A,100HZ	
3	CNY01	AA39-00100E	LEAD CONNECTOR-ASSY;,4P,600MM,YBNH250-04	
3	CPC+CC	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
3	SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3		AA97-12449A	ASSY AUTO-CONTROL;29Z6,K55A,PAL	S.N.A
4	DZY03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	DZY04	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4	LY01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	PCB	AA41-00651A	PCB-CONTROL;CS29Z7HF,FR-1,1L,A,1.6T,330X	S.N.A
4	RY02	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RY03	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RY04	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RY05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RY06	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3		AA96-00935B	ASSY COVER P-COVER CONTROL;29Z6,CIS,HIPS	
4	KC+CC	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
4		AA63-60001R	SPACER-FELT;-,FELT,-,-,-,-,T0.35,-,200X1	S.N.A
4		AA64-02662A	KNOB-CONTROL;Z7,ABS,HB,G3676,S104M+W971	
4		AA63-00569B	COVER-CONTROL;29Z6,HIPS,HB,G4309,DGN-118	S.N.A
⚠ 2		AA96-20130H	ASSY POWER CORD;-,CP2/NO(4.0R),H/S 500MM	S.N.A
3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
3		AA39-10003B	CBF POWER CORD;-,KJP-140,KLCE-2F,2.4m,HO	
3		AA61-20284A	HOLDER;P-CORD,PP;-,-,-,BLK,V0,KE-002	S.N.A
2		AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
2		AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
2		AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5	
3	LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,EER2	
3	LH02	AA27-40003L	COIL HORIZ. WIDTH;-,1.0mH,DR14x20,2UEW0.	
3	RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP,3.9x12	
3	WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3P,200,YFH800-03,S,	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3		AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A
4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY05	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY06	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY07	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	EY08	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY09	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	GTH01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GTH02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GTH03	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A
2		AA94-11187A	ASSY PCB MAIN;CS29Z6HPJX/BWT,K55A	
3	C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-,	
3	C806	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
3	C820	2401-003419	C-AL;2200uF,20%,50V,WT,TP,16X35.5mm	
3	CABLE	AA39-30007B	CBF IF;-,T,150mm,1365#26	
3	CN301	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
3	CN502	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
3	CN702	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
3	CN702A	AA39-00114C	LEAD CONNECTOR-ASSY;,12P,500MM,35155-120	
⚠ 3	D801S	AA96-00276C	ASSY H/S;-,BRIDGE ,AA62-00052A,GSIB660,K	S.N.A
4		AA62-00052A	HEAT SINK-PS;-,-,-,SILVER,HOLE 18.5mm, 2	S.N.A
4		AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
4		0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ 3	GT804S	AA39-20010C	LEAD CONNECTOR-ASSY;,1P,600,YFH800-01,S,	
3	HC401	BP96-00159A	ASSY HEAT SINK P;H/S,SCREW,FJL6920,FMP-3	S.N.A
4	CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
4	CIS	BP62-00015A	HEAT SINK-PS;WT-36Z4HR,A1050S,T2.0,86,80	S.N.A
4	CIS	BH73-00028B	SILICON/RUBBER-HS;TV ALL,SILICON,26*30*T	S.N.A
4	CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
4	CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
4	CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
3	HC801	AA96-00475A	ASSY H/S;-,REGULATOR,AA62-00066B,FML-G12	S.N.A
4		AA62-00066B	HEAT SINK;D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
4		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
3	IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		1204-000517	IC-VERTICAL DEF;LA7845,SIP,7P,-,PLASTIC	
4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
4		AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
3	IC602	AA96-50369D	ASSY H/S;-,SOUND,AA62-30181F,TDA7269,HER	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P	
4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
4		AA62-30181F	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
⚠ 3	IC801S	AA96-50371H	ASSY H/S;-,SMPS,AA62-30181H,5Q1565RF,HER	S.N.A
4		AA61-11028A	BRACKET;-,SECC,T1.0,-,-,-,-	S.N.A
4		AA62-30181H	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,50MM,-	S.N.A
4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
4		1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF	
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
3	IC805	AA96-00243K	ASSY H/S;-,REGULATOR,AA62-000450A,KA78R0	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
4		1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
3	IC901	AA97-13892A	ASSY MICOM;,K55A,SDA555X,SIM-832M4,02122	
4		AA09-00041A	IC MICOM;,SDA555X-OTP,3.3V,-,128K,SDIP,-	S.N.A
3	JA701	3722-001884	JACK-SCART;42P,-,SNPB,BLK,-	
3	JA702	3722-001767	JACK-PIN;2P(9P),-,NI,WHI/RED,-	
⚠ 3	LR402S	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ 3	LR403S	AA27-00070A	COIL LINEARITY;-,7uH,YL81 DR1518,11mm,17	
⚠ 3	LR404S	AA27-40001S	COIL HORIZ. WIDTH;-,110uH,SB-5S8202.6,PI	
3	Q402	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
3	Q804	BH99-00007S	ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A
4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
4	CIS	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
4	CIS	BH62-00007A	HEAT SINK-TR;-,T1.0,L20*H30,CDA	S.N.A
⚠ 3	RL801S	3501-001053	RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5	
3	T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
⚠ 3	T444S	AA26-00170A	TRANS FBT;FUJ-29H002F,29F,1.95MH,FERRIT	
⚠ 3	T801S	AA26-00178A	TRANS SWITCHING;EER5345,K55A,PAL,CIS,160	
⚠ 3	TU02S	AA40-00084A	TUNER;TCPS3000PC16B(S),PAL ,181CH,38.9MH	
3	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	

Level	Loc. No.	Code No.	Description ; Specification	Remark
3		AA95-03091A	ASSY SUB-PCB,FEATURE BOX;,K55A, ,PAL	
4	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
4	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
4	CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
4	CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
4	CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
4	DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
4	DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4	DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
4	EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	
4	IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC	
4		AA97-12148A	ASSY SMD;,K55A PAL	S.N.A
5	DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
5	DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
5	DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
5	DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
5	DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
5	DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
5	DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	DC34	2203-000896	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
5	DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
5	DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
5	DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
5	DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
5	DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
5	DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
5	DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
5	DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
5	DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
5	DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
5	DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
5	DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
5	DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
5	DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
5	DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
5	DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
5	DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
5	DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
5	DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
5	DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
5	DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
5	DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
5	DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
5	DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
5	DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
5	DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
5	DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
5	DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
5	DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
5	DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
5	DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
5	DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
5	DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
5	DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
5	DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
5	DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
5	DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
5	DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
5	DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
5	DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
5	DR68	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	DR69	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	DR70	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
5	DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
5	DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
5	DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
5	DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
5	EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
5	EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	EC29	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
5	EC30	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
5	EC31	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
5	EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC34	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
5	EC35	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
5	EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
5	EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
5	EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
5	EC58	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	EC62	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
5	EC63	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
5	EC64	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
5	EC65	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
5	EL04	3301-001082	CORE-FERRITE BEAD;AB,600HM,3.2X2.5X1.3MM	
5	EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	EL06	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
5	EL07	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,	
5	EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.50HM,0.	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
5	EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	ER01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
5	ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
5	ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	ER22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	ER29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	ER30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	ER31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	ER32	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
5	ER33	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
5	ER34	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
5	ER35	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
5	ER36	2007-000293	R-CHIP;100OHM,5%,1/8W,DA,TP,3216	
5	IC01	1204-001938	IC-DECODER;VSP9407B-B11,MQFP,80P,14X14MM	
5	IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
5	IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
5	IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH ,S	
5	IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
5	PCB	AA41-00644B	PCB-PAL FERTURE BOX;CS29Z6,FR-4,4L,B,1.6	S.N.A
5	SC29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SC31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SC33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	SC47	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
5	SC48	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
5	SC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	SR30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SR31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SR32	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SR33	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SR34	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	SR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	SR36	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
5	SR37	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
5	TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
5	TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
5	TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	TD01	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
5	TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
5	TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
5	TR01	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	TR03	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	TR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
5	TR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
3		AA97-12466A	ASSY ROBOT-MAIN;CS29Z6,K55A	S.N.A
4	C423	2306-000272	C-FILM,MPPF;820nF,5%,400V,BK,29x25.5x18.	
4	C426	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
4	C803	2401-002227	C-AL;330uF,20%,450V,GP,BK,35x45,10	
4	C815	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	
4	CN902	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
⚠ 4	CR405S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	
⚠ 4	CR406S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	
⚠ 4	CR407S	2301-001398	C-FILM,MPPF;3.3nF,5%,2kV,TP,29x8.5x1.5mm	
⚠ 4	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 4	CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 4	CY802S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ 4	FP801S	3601-000297	FUSE-CARTRIDGE;250V,5A,TIME-LAG,GLASS,5.	
⚠ 4	IC401	1202-000103	IC-VOLTAGE COMP.;393,DIP,8P,300MIL,DUAL,	
4	IC601	1204-001971	IC-SOUND PROCESSOR;MSP3411G-P0-B11,DIP,5	
4	IC803	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P,-,PLA	
4	IC902	1103-001177	IC-EEPROM;24WC16,2048x8Bit,DIP,8P,-,-,2.	
4	L808	AA27-00098A	COIL CHOKE;-,-,24uH,10%,-,0.1,3.0A,DR10X	
⚠ 4	LR405S	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
⚠ 4	LX801S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 4	LX802S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 4	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 4	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ 4	PT801S	1404-001026	THERMISTOR-PTC;7ohm,20%,-,290V,25A,-,ST	
⚠ 4	TU01S	AA40-00083A	TUNER;TCLS3101PD16A(S),PAL B/G,D/K,I,M,1	
4		AA97-12467A	ASSY AUTO-MAIN;CS29Z6,K55A	S.N.A
5	C101	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C102	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C104	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
5	C105	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C106	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
5	C107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C108	2401-003578	C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
5	C109	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
5	C110	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
5	C111	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
5	C112	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C113	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
5	C116	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C201	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C202	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
5	C203	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
5	C204	2202-000106	C-CERAMIC,MLC-AXIAL;1.5nF,20%,16V,Y5P,TP	
5	C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C207	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C239	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C302	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
5	C303	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
5	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
5	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
5	C306	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
5	C307	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
5	C308	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
5	C401	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
5	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
5	C403	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
5	C404	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
5	C408	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
5	C409	2301-001385	C-FILM,PPF;30nF,5%,630V,TP,20x15.5x10.5,	
5	C411	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
5	C412	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
5	C413	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
5	C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
5	C415	2301-000203	C-FILM,PEF;2.7nF,5%,100V,TP,7x3.0x6.5mm,	
5	C416	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
5	C420	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
5	C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
5	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
5	C424	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
5	C425	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
5	C432	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
5	C601	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
5	C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
5	C603	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
5	C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
5	C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
5	C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
5	C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
5	C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
5	C615	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C619	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C620	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C621	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C622	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C623	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C624	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C625	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C626	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C627	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C628	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C629	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C630	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C631	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C632	2201-000370	C-CERAMIC,DISC;0.22NF,10%,50V,Y5P,TP,4X3	
5	C633	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
5	C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C636	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C637	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C638	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C639	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C640	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C641	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C642	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
5	C643	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
5	C645	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
5	C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5	
5	C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
5	C650	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
5	C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C652	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
5	C654	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
5	C655	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
5	C656	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
5	C657	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
5	C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C660	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
5	C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
5	C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
5	C804	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
5	C805	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
5	C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
5	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
5	C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
5	C810	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
5	C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
5	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C813	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.	
5	C814	2201-002028	C-CERAMIC,DISC;0.47NF,10%,2KV,Y5P,TP,7.5	
5	C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
5	C817	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
5	C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
5	C819	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
5	C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
5	C822	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
5	C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
5	C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
5	C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
5	C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
5	C828	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
5	C830	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
5	C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
5	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
5	C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
5	C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
5	C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
5	C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
5	C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
5	C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
5	C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
5	C904	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
5	C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
5	C906	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
5	C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
5	C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
5	C910	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
5	C911	2201-000980	C-CERAMIC,DISC;0.03NF,5%,50V,C0G,TP,5X3M	
5	C912	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
5	C913	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C915	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C917	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
5	C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
5	C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C920	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
5	C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
5	C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
5	C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
5	C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
5	CN302	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
5	CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
5	CN901	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
5	CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
5	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 5	D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 5	D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
5	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D801	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D802	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 5	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 5	D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 5	D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 5	D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
5	D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
5	D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
5	D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
5	D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
5	D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
5	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
5	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
5	DZ304	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
5	DZ305	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
5	DZ307	0403-001118	DIODE-ZENER;MTZ30A,32V,26.99-28.39V,500m	
5	DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
5	DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
5	DZ404	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ602	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
5	DZ603	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ604	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ605	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ607	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
5	DZ608	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
5	DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
5	DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
5	DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
5	DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
5	DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
5	DZ807	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
5	DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ909	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ910	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ911	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	DZ912	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
5	EL201	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL202	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL203	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL204	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EL808	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
5	EY302	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY303	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY403	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY404	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY405	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY406	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY407	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY408	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY409	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY410	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY411	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY412	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY413	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY414	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY415	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY417	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY418	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY419	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY420	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY421	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY422	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY423	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY424	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY425	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY426	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY429	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY430	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY431	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY432	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY433	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY434	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY435	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY436	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY437	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY439	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY441	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY446	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY447	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY603	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY604	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY701	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY702	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY703	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY704	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY705	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY706	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY801	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY802	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY803	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY804	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY805	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY806	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY809	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY810	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY811	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY812	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY813	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY814	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY815	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY816	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY817	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY820	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY824	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY825	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY828	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY829	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY830	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY831	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY832	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY833	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY835	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY836	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY837	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY838	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY839	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY840	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY841	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY842	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY844	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY845	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY846	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY848	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY850	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY851	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY853	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY854	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY855	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY856	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY857	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY858	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY859	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY860	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY861	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY862	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY864	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY865	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY871	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	EY872	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
5	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
5	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 5	FA801S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
⚠ 5	FA802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ 5	FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
5	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT409	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT410	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT411	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	GT412	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
5	HIC401	AA13-00094A	IC HYBRID;-,DDRI001A,SIP,5P,-,TP	
5	IC202	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
5	IC402	1203-000243	IC-POSI.FIXED REG.;7812A,TO-220,3P,-,PLA	
5	IC804	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
5	IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
5	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
5	J709	2001-000376	R-CARBON;15OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
5	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
5	L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
5	L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
5	L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
5	L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
5	L203	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
⚠ 5	L403	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
5	L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	L409	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	L410	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
5	L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
5	L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
5	L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
5	L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L612	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	L613	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L615	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
5	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
5	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
5	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
5	L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
5	L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
5	L807	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
5	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
5	L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
5	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
5	L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
5	L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
5	L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
5	L906	2701-000215	INDUCTOR-AXIAL;8.2uH,10%,2.5x3.4mm	
5	L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
5	L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
5	L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm	
5	PCB	AA41-00707B	PCB-MAIN;CS29Z6HP,FR-1,1L,B,1.6T,330X245	S.N.A
5	Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
5	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
5	Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
5	Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
5	Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	Q914	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
5	R101	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R107	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R108	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R301	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
5	R303	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
5	R304	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
5	R305	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
5	R306	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
5	R307	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
5	R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
5	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R314	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R315	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
5	R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
5	R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
5	R403	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
5	R405	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
5	R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
5	R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
5	R411	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
5	R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
5	R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
5	R415	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
5	R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
5	R418	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R420	2004-001987	R-METAL(S);4.3Kohm,1%,1/2W,AA,TP,2.4x6.4	
5	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R422	2008-000251	R-FUSIBLE(S);0.27ohm,5%,2W,AF,TP,3.9x10m	
5	R423	2001-001055	R-CARBON(S);1.8KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
5	R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
5	R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
5	R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
5	R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
5	R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
5	R432	2001-001164	R-CARBON(S);56KOHM,5%,1/2W,AA,TP,2.4X6.4	
5	R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
5	R434	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
5	R435	2003-001042	R-METAL OXIDE(S);5.6Kohm,5%,2W,AF,TP,3.9	
5	R440	2004-001893	R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5m	
5	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R607	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R608	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R609	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R617	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
5	R618	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R636	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R637	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R638	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R639	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R710	2001-000376	R-CARBON;15OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R801	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
5	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
5	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
5	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
5	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R807	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
5	R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R809	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R811	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R813	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R815	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
5	R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
5	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
5	R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	
5	R821	2004-001891	R-METAL(S);133Kohm,1%,1/2W,AA,TP,2.5x6.5	
5	R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R824	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
5	R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm	
5	R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9X12MM	
5	R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
5	R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x	
5	R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
5	R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R906	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R908	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R910	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R912	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R915	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R916	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R917	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R925	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R926	2001-000793	R-CARBON;470HM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R945	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R946	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R947	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R948	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R951	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R954	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R955	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R958	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R961	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R962	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R965	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R967	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R968	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R981	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R982	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R983	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R984	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5	R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 5	RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
⚠ 5	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 5	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
5	X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
3		AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A
3		AA39-20536G	LEAD CONNECTOR-ASSY;,1P,60MM,F,F,1617#22	
2		AA94-11730A	ASSY PCB MISC-MASTER;Z6,Z7Z9,K55A,S57A,P	
3	GTAY01	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,600MM,YFH800-	
3	HP+PCB	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
3	MPP+LP	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
⚠ 3	SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
3		AA97-05539A	ASSY AUTO-MASTER;WS36Z48D,KS4A,PAL	S.N.A
4	EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	GTY05	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GTY06	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GTY07	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GTY08	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GTY09	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GTY10	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	PCB	AA41-00521A	PCB-MASTER S/W;CS32Z4,FR-1,1L,A,1.6T,245	S.N.A
3		AA61-00719B	HOLDER-MASTER;T6,W3,HIPS V0,BLK,J52A	S.N.A
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
2		AA94-11731A	ASSY PCB MISC-LED;CS29Z6HPJX/BWT,K55A	
3	CN01	AA39-20069A	LEAD CONNECTOR-ASSY;,5P,500,YBNH025-05,6	
3	CY01	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
3	LD01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
3	RM01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3		AA97-12478A	ASSY AUTO-LED;CS29Z6,K55A	S.N.A
4	DC01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DC02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	PCB	AA41-00702A	PCB-LED;WS32Z6HF,FR-1,1L,A,1.6T,245X245,	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
4	RY01	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	

ASSY COVER REAR

1		AA90-03248B	ASSY COVER REAR;CS29Z6HPJX/BWT	S.N.A
2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
2		AA64-02745C	CABINET BACK;29Z6,ABS,VO,G4309,SVM2012	

ASSY COVER FRONT

1		AA90-03245B	ASSY COVER FRONT;CS29Z6HPJ/BWT	S.N.A
2	BRK+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	
2	CA+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
2	CB+TBA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
2	CC+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
2	CRT+CF	AA60-10050V	SCREW-ASSY;-,SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
2	D-COIL	AA65-30017A	CLAMPER CORE-D,COIL;-,NYLON-66,V0,-,NTR,	S.N.A
2	PP+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
2	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
2	TBA+RJ	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
2		AA96-00932D	ASSY COVER P-FRONT;29Z6,CS29Z6HF,ABS HB0	
3	DP+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
3	KNOPOW	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
3		AA64-02753A	INDICATOR LED;29Z6,ACRYL,HB,CLEAR	S.N.A
3		AA64-70117B	BADGE-BRAND;-,AL,-,-,L65,R2000,SILVER,SS	S.N.A
3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
3		AA60-00091C	SPACER-FELT;-,FELT,230X10,-,-,BLK,T1.0,-	S.N.A
3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
3		AA64-02752A	WINDOW-RMC;29Z6,PC,VO,VIOLET	S.N.A
3		AA60-00091G	SPACER-FELT;-,FELT,200X10,-,-,BLK,T0.5,-	S.N.A
3		AA64-02744D	CABINET-FRONT;CS29Z6HF,ABS,HB0690M,G4309	S.N.A
3		AA64-02750A	DECORATION-POWER;29Z6,ABS,HB,GRAY,AL	
3		AA64-02751B	KNOB-POWER;29Z6,PC,VO,VIOLET,MASTER	
2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	
2		AA73-00017A	RUBBER-CAP;29Z7,SILICONE RUBBER,WHT	S.N.A
2		AA96-00967D	ASSY COVER P-RACK;TR-29Z6,SVM2012,DIY,SP	
2		AA91-00507A	ASSY HOLDER SPK;-,-,8OHM/15W,-,ASSY HOLD	
2		AA65-00019A	CLAMPER CORE-D,COIL;25-34,NYLON 66,V2,N	S.N.A
2		AA63-60004K	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,BLK,T2	S.N.A
2		AA61-10054A	BRACKET-CRATER;6277,STS304,T0.5,-,-,-,-	S.N.A

ASSY CPT

1		AA91-03134A	ASSY CPT;CT-29Z4HR	S.N.A
2		AA91-02173Q	ASSY CPT;A68QCP891X004,29,+380MG,ITC,CT	S.N.A
⚠ 3		AA03-00076A	CRT COLOR;A68QCP891X004(C),+380mG,0.315m	
2		AA98-70011D	ASSY TBC WIRE(P);-,29',NTSC,PAL,2P-WH,-	S.N.A
2		AA27-00128A	COIL DEGAUSSING;-,-,-,-,50T,7,-,29inch,2	

ASSY P/MATERIAL

1		AA92-05371B	ASSY P/MATERIAL;CS29Z6HFGX/BWT	S.N.A
2		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A

ASSY ACCESSORY

1		AA92-06199A	ASSY ACCESSORY;29Z6,RUSSIA,K55A	S.N.A
2	1	AA68-02479A	MANUAL USERS;CS29Z7HP,RUS,K55A,PIP,TTX	
2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	S.N.A
2		AA59-00266D	REMOCON;TM63,HERCULES,45,SAMSUNG,EX,RUSS	
3		2802-000194	RESONATOR-CERAMIC;8MHz,1.0%,TP,8.5x4.5x5	
3		AA09-00275A	IC MICOM;Z86L8808SSC-R51PX,SOP,ST,SZTM-8	
2		AA68-00952A	CARD-COUPON;-,A/P100(G),AA68-00949A,-,-,	S.N.A
2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
2		AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
2		AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	S.N.A

ASSY LABEL

1		AA92-05518C	ASSY LABEL;29Z6,K55A,RUSSIA	S.N.A

ASSY BOX

1		AA92-05368B	ASSY BOX;CS29Z6HPJX/BWT	S.N.A